

Voltage Range - 20 to 40 V Forward Current - 3 Ampere

# **SCHOTTKY BARRIER RECTIFIER**

#### **FEATURES**

- Fast switching
- Low forward voltage, high current capability
- Low power loss, high efficiency
- High current surge capability
- High temperature soldering guaranteed:

250°C/10 seconds,0.373"(9.5mm) lead length At 5 lbs.(2.3kg) tension

### **MECHANICAL DATA**

Case: Transfer molded plastic


■ Epoxy: UL94V-0 rate flame retardant

Polarity: Color band denoted cathode end

Lead: Plated axial lead, solderable per MIL-STD-202E method 208C

Mounting position: Any

■ Weight: 0.042ounce, 1.19 gram



### MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

■ Ratings at 25 °C ambient temperature unless otherwise specified Single Phase, half wave, 60Hz, resistive or inductive load For capacitive load derate current by 20%.

		SYMBOLS	1N5820	1N5821	1N5822	UNIT
Maximum Repetitive Peak Reverse Voltage		$V_{RRM}$	20	30	40	Volts
Maximum RMS Voltage		$V_{RMS}$	14	21	28	Volts
Maximum DC Blocking Voltage		$V_{DC}$	20	30	40	Volts
Maximum Average Forward Rectified Current 0.375" (9.5mm) lead length at $T_L = 95$ °C		I <sub>(AV)</sub>	3.0			Amps
Peak Forward Surge Current 8.3mS single half sine-wave superimposed on rated load (JEDEC method)		I <sub>FSM</sub>	80			Amps
Maximum Instantaneous Forward Voltage (Note 1) at	3.0A	V <sub>F</sub>	0.475	0.500	0.525	Volts
	9.4A		0.850	0.900	0.950	
Maximum DC Reverse Current at rated DC Blocking Voltage at (Note 1)	$T_A = 25^{\circ}C$	т	0.5			mA
	T <sub>A</sub> = 100°C	$I_R$	20			
Typical Junction Capacitance (NOTE 2)		$C_{J}$	250			pF
Typical Thermal Resistance (NOTE 3)		$R_{ heta JL}$	15			°C/W
Operation and Storage Temperature Range		T <sub>J</sub> .T <sub>STG</sub>	(-55 to +125)			$^{\circ}\mathbb{C}$

#### Notes:

- 1. Pulse test 300µs pulse width,1% duty cycle
- 2. Measured at 1.0MHz and applied reverse voltage of 4.0 Volts
- 3. Thermal resistance from junction to ambient P.C.B .mounted with 0.375"(9.5mm)lead length with 2.5"×2.5" (63.5×63.5mm) copper pads


Email: sales@micindia.com Website: www.micindia.com





Voltage Range - 20 to 40 V Forward Current - 3 Ampere

## **SCHOTTKY BARRIER RECTIFIER**

## RATING AND CHARACTERISTIC CURVES 1N5820 - 1N5822











FIG.4-TYPICAL REVERSE



#### Disclaimer

All product, product specifications and data are subject to change without notice to improve reliability, function or design or otherwise.

Email: sales@micindia.com Website: www.micindia.com